Lamp		Gear system for best performance				Alternative gear system for good performance			
Commercial name	Technical name	Ballast	Picture	Ignitor, 18	Capacitor, 17	Ballast	Picture	Ignitor, 18	Capacitor, 17
Mini MasterColour	CDM-Tm 20W	PrimaVision mini 20 CDM	1						
Mini MasterColour	CDM-Tm 35W	PrimaVision mini 35 CDM	1						
MASTER Colour CDM-TC	CDM-TC 35W	PrimaVision 035 CDM	3,4			PrimaVision 2x035 CDM	3,4		
MASTER Colour CDM-R111	CDM-TC 70W	PrimaVision 070 CDM	3,4						
MASTER Colour CDM-T	CDM 35W	PrimaVision 035 CDM	3,4			BMH 35 L407-ITS	10	SND-58 (SUD-40)	6uF/250V
MASTER Colour CDM-TD	CDM 70W	PrimaVision 070 CDM	3,4			BMH 70 L407-ITS	10	SND-58 (SUD-40)	12uF/250V
MASTER Colour CDM-TP	CDM 150W	PrimaVision 150 CDM	3,4			BSN 150 L407-ITS	9	SND-58 (SUD-40)	18uF/250V
MASTER Colour CDM-R			3,4						
MASTER SDW-TG	SDW-TG 50W	PrimaVision 50W SDW-TG	5						
	SDW-TG 100W	PrimaVision 100W SDW-TG	5						
MASTER SDW-T	SDW-T 35W	BSL 35 L307	16	CSLS-35	6uF/250V				
	SDW-T 50W	BSL 50L307	16	CSLS-50	9uF/250V				
	SDW-T 100W	BSL 100 L307	16	CSLS-100	14uF/250V				
MHN/W-TD	MHN/W-TD 70W	BMH 70 L407-ITS	10	SND-58 (SUD-40)	12uF/250V				
	MHN/W-TD 150W	PrimaVision 150 CDM	3			BSN 150 L407-ITS	9	SND-58 (SUD-40)	18uF/250V
	MHN/W-TD 250W	BSN 250 L407-ITS	9	SND-58 (SUD-40)	18uF/250V				
MASTER Colour City CDO-T(T)/ET	CDO 70W	Prima/DynaVision 070 SON/CDO	2,7			BSN 70 L407-ITS	9	SND-57 (SUD-10)	12uF/250V
	CDO 100W	Prima/DynaVision 100 SON/CDO	2,7			BSN 100 L407-ITS	9	SND-58 (SUD-40)	12uF/250V
	CDO 150W	Prima/DynaVision 150 SON/CDO	2,7			BSN 150 L407-ITS	9	SND-58 (SUD-40)	18uF/250V
MASTER SON-T PIA PLUS	SON 50W	BSN 50 L407-ITS	9	SND-57 (SUD-10)	10uF/250V	BSN 50 L33-TS	9	SND-57 (SUD-10)	10uF/250V
MASTER SON PIA PLUS	SON 70W	Prima/DynaVision 70 SON/CDO	2,7			BSN 70 L407-ITS	9	SND-57 (SUD-10)	12uF/250V
MASTER SON-T PIA	SON 100W	Prima/DynaVision 100 SON/CDO	2,7			BSN 100 L407-ITS	9	SND-58 (SUD-40)	12uF/250V
Pro SON	SON 150W	Prima/DynaVision 150 SON/CDO	2,7			BSN 150 L407-ITS	9	SND-58 (SUD-40)	18uF/250V
	SON 250W	BSN 250 L407-ITS	9	SND-58 (SUD-40)	32uF/250V	BSN 250 L33-TS	9	SND-58 (SUD-40)	32uF/250V
	SON 400W	BSN 400 L407-ITS	9	SND-58 (SUD-40)	45uF/250V	BSN 400 L33-TS	9	SND-58 (SUD-40)	45uF/250V
	SON 600W	BSN 600 L407-ITS	9	SND-58	60uF/250V				
	SON 600W-400V	BSN 600 L309-ITS	9	SND-88/SND-89	20uF/450V				
	SON 1000W	BSN 1000 L78	9	SN-56/SN-59	100uF/250V				
SON-I	SON-I 50W	BSN 5070 L407-TS	9	-	10uF/250V	BSN 50 L33-TS	9	-	10uF/250V
	SON-I 70W	BSN 5070 L407-TS	9	-	12uF/250V	BSN 70 L33-TS	9	-	12uF/250V
SON-H Pro	SON-H 110W	BHL 80125 L407	11	-	10uF/250V	BHL 80125 L48	11	-	10uF/250V
	SON-H 220W	BHL 250 L307	11	-	18uF/250V	BHL 250 L40	11	-	18uF/250V
	SON-H 350W	BHL 400 L307	11	-	25uF/250V	BHL 400 L40	11	-	25uF/250V
MASTER HPI PLUS	HPI PLUS 250W BU	BHL 250 L307(-TS)	11	SI-51	18uF/250V	BSN 250 L407-I(TS)	9	SND-58 / SI-51	32uF/250V
	HPI PLUS 400W BU	BHL 400 L307(-TS)	11	SI-51	25uF/250V	BSN 400 L407-I(TS)	9	SND-58 / SI-51	45uF/250V
	HPI PLUS 400W BUS	BHL 400 L307(-TS)	11	-	25uF/250V	BSN 400 L407-I(TS)	9	-	45uF/250V
HPI-T Pro	HPI-T 1000W/230V	BHL 1000 L78	11	SI-52	65uF/250V				
	HPI-T 2000W/220-240V	BHL 2000 L78	11	SI-52	125uF/250V				
	HPI-T 2000W/380-415V	BHL 2000 L76	11	SI-54	35uF/450V				
HPL-N	HPL-N 50W	BHL 5080 L407	11	-	7uF/250V	BHL 5080 L48	11	-	7uF/250V
HPL-N	HPL-N 80W	BHL 5080 L407	11	-	8uF/250V	BHL 5080 L48	11	-	8uF/250V
HPL-N	HPL-N 125W	BHL 80125 L407	11	-	10uF/250V	BHL 80125 L48	11	-	10uF/250V
HPL-N	HPL-N 250W	BHL 250 L307	11	-	18uF/250V	BHL 250 L40	11	-	18uF/250V
HPL-N	HPL-N 400W	BHL 400 L307	11	-	25uF/250V	BHL 400 L40	11	-	25uF/250V
HPL-N	HPL-N 1000W/230V	BHL 1000 L78	11	SI-52	65uF/250V				
MASTER MHN-SA	MHN-SA 1800W/230V	BMH 1800 L78	10	SN-56/SN-59	200uF/250V				
MASTER MHN-SA	MHN-SA 1800W/400V	BHD 2000 L76	12	380MZN2000	75uF/450V				
MASTER MHN-SA	MHN-SA 2000W/400V	BHD 2000 L76	12	380MZN2000	70uF/450V				
MASTER MHN-LA	MHN-LA 1000W/230V	BSN 1000 L78	9	SN-56/SN-59	100uF/250V				
MASTER MHN-LA	MHN-LA 2000W/400V	BHD 2000 L76	12	380MZN2000	65uF/450V				
MHN-SB 2000 W Pro	MHN-SB 2000W	BHD 2000 L76	12	SN-56/SN-59					
SOX Pro	SOX 35W	EXC 35	8			BSX 35 L81	13,14	SX-26	8uF/250V
SOX Pro	SOX 55W	EXC 55	8			BSX 55 H26	13,14	SX-72	5.7uF/450V
SOX Pro	SOX 90W	BSX 90 H26	13,14	SX-70	7.6uF/300V	BSX 90 L40	13,14	SX-76	10uF/230V
SOX Pro	SOX 135W	BSX 135 H96	13,14	SX-74	6.8uF/420V				
SOX Pro	SOX 180W	BSX 180 H96	13,14	SX-73	4.4uF/650V				
MASTER SOX-E	SOX-E 18W	BSX 18 L81	13,14	SX-26	4.5uF/250V				
MASTER SOX-E	SOX-E 26W	BSX 26 L81	13,14	SX-26	6uF/250V	BSX 26 L40	13,14	SX-26	6uF/230V
MASTER SOX-E	SOX-E 36W	EXC 36	8			BSX 36 H66	13,14	SX-72	4.4uF/300V
MASTER SOX-E	SOX-E 66W	EXC 66	8			BSX 90 H40	13,14	SX-76	7.6uF/300V
MASTER SOX-E	SOX-E 91W	EXC 91	8			BSX 91 H96	13,14	SX-74	5,2uF/300V
MASTER SOX-E	SOX-E 131W	BSX 131 H96	13,14	SX-131	3.4uF/650V				
MASTER CosmoWhite 65	CPO-TW	HID-PV 65 CPO-TW	6						
MASTER CosmoWhite 140	CPO-TW	HID-PV 140 CPO-TW	6						
MASTER CosmoGold 60	CPO-TG	HID-PV 60 CPO-TG	6						
MASTER CosmoGold 140	CPO-TG	HID-PV 140 CPO-TG	6						
				no ignitor for QL but power coupler					
QL 55W Twist Base	QL 55W	HF-Generator QL 55W S/03	15	Power Coupler QL 55W Twist base					
QL 85W Twist Base	QL 85W	HF-Generator QL 85W 200-277V	15	Power Coupler QL 85W Twist base					
QL 165W Twist Base	QL 165W	HF-Generator QL 165W S/01	15	Power Coupler QL 165W Twist base					